

Banana Pi M2 Ultra als headless VDR

Quellen:

- [Getting started with Armbian](#)
- [Armbian Documentation](#)
- [Bananapi M2U / Berry](#)
- [Mirror of dl.armbian.com](#)
- [Mirror of archive.armbian.com](#)
- [USBImager](#)
- [Building Armbian](#)

funktionierende Images:

Bananapi.org

- https://wiki.banana-pi.org/Banana_Pi_BPI-M2U

Login: root/bananapi

uname -a -> Linux bpi-iot-ros-ai 3.10.108-BPI-M2U-Kernel #2 SMP Sun Apr 19 14:29:27 HKT 2020

armv7l GNU/Linux

cat /etc/os-release -> PRETTY_NAME=„Debian GNU/Linux 9 (stretch)„

Netzwerk funktioniert nicht!

SD-Karte befüllen:

wget

```
https://armbian.systemonachip.net/archive/bananapim2ultra/archive/Armbian_20.11_Bananapim2ultra_buster_current_5.8.16_minimal.img.xz
```

```
xz -d Armbian_20.11_Bananapim2ultra_buster_current_5.8.16_minimal.img.xz
```

```
sudo dd if=Armbian_20.11_Bananapim2ultra_buster_current_5.8.16_minimal.img of=/dev/sdc bs=1M
```

```
# oder via USBImager direkt die *.xz Datei auf eine SD-Karte schreiben
```

```
# oder
```

```
# xzcat Armbian_20.11_Bananapim2ultra_buster_current_5.8.16_minimal.img.xz | sudo dd bs=1M of=/dev/sdc
```

Die erste Boot-Phase ist sehr lang! Bis zu einem SSH-Login kann es mehr als 10 Minuten dauern.

Building Armbian

```
apt-get -y -qq install git
```

```
git clone --depth 1 https://github.com/armbian/build
```

```
cd build
./compile.sh

# fertiges Image liegt dann unter: "build/output/images/"
# Automatischer Build für ein Standard-Image:
01: ./compile.sh BOARD=bananapim2ultra BRANCH=current RELEASE=buster
BUILD_MINIMAL=yes BUILD_DESKTOP=no KERNEL_ONLY=no KERNEL_CONFIGURE=prebuilt
COMPRESS_OUTPUTIMAGE=sha,gpg,img
02: ./compile.sh BOARD=bananapim2ultra BRANCH=current RELEASE=focal
BUILD_MINIMAL=yes BUILD_DESKTOP=no KERNEL_ONLY=no KERNEL_CONFIGURE=prebuilt
COMPRESS_OUTPUTIMAGE=sha,gpg,img
```

Konfig

```
sudo su
resize2fs /dev/mmcblk0p1
#
apt-get install aptitude armbian-config
apt-get purge locales
aptitude install locales
dpkg-reconfigure locales
# --> en_US.UTF-8
#
#change /boot/armbianEnv.txt to have "verbosity=7" and "console=serial"
mcedit /boot/armbianEnv.txt
#
```

```
mcedit /etc/apt/sources.list

deb http://deb.debian.org/debian bullseye main contrib non-free
deb-src http://deb.debian.org/debian bullseye main contrib non-free

deb http://deb.debian.org/debian-security/ bullseye-security main contrib
non-free
deb-src http://deb.debian.org/debian-security/ bullseye-security main
contrib non-free

deb http://deb.debian.org/debian bullseye-updates main contrib non-free
deb-src http://deb.debian.org/debian bullseye-updates main contrib non-free
```

From:
<https://www.von-thuelen.de/> - Christophs DokuWiki

Permanent link:
https://www.von-thuelen.de/doku.php/wiki/projekte/bananapi_m2u_vdr/uebersicht?rev=1639312722

Last update: 2021/12/12 13:38

